Guide to installing your Double-sided upgrade for Magicard Ultima printers

Installing a Double-sided upgrade to your Ultima printer can be done in two ways, both through your printer driver.

If the printer is connected to an Internet-enabled PC: By downloading the Double-sided upgrade file securely from our webserver.

If the printer cannot be connected to an Internet-enabled PC: By downloading the Double-sided upgrade file from your support account and installing it offline from a connected PC.

Online Installation

Open the Magicard Ultima driver in the **<Devices and printers>** area of your Windows OS and then open **<Adjust printer options>**

- 🗆 X

← Settings
๗ Magicard Ultima (V2)
Manage your device
Printer status: Idle
Open print queue Set as default
Print a test page
Run the troubleshooter
Printer properties
Printing preferences
Hardware properties
Have a question? Get help

Magicard Ultima (V2) Printing Pret	tima	
Printer	Duplex printing	Front only
	Card orientation	Landscape ~
Each Card front	Card size	CR80 card V
Card back	_	Bend Solution
Encoding		1036 x 664 pixels
Image		87.7 x 56.1 mm
Advanced	Number of copies	1
Save	Printer upgrade(s).	Printer status
About Help] [OK Cancel Apply

On the first <**Printer tab>** click <**Printer upgrade(s)...>** button

Navigate to the **<Double sided upgrade>** tab and click the **<Install>.** This will bring up a dialogue showing your printer connecting to the secure server to retrieve your upgrade file.

	Double sided	
	L.	
Orde	er	
Insta	all	
Offline I	nstall	
	Orde Insta	Order Install Offline Install

Once complete your will receive a confirmation dialog once your printer has been upgraded.



To check your printer has been successfully upgraded navigate to your **<printer tab>** and the **<Duplex printing option>** will be enabled as well as the **<Card back tab>** in the printer driver.

Magicard Ultima (V2) Printing Prefe	tima	×
Printer	Duplex printing	Front only
	Card orientation	Landscape ~
Eard front	Card size	CR80 card ~
Card back]	Bend Solution
Encoding		1036 x 664 pixels
Image		87.7 x 56.1 mm
d Advanced	Number of copies	1
Save	Printer upgrade(s)	Printer status
About Help		OK Cancel Apply

Offline installation

If your printer cannot be connected to an Internet-enabled computer it is possible to perform an offline installation.

To do this you will need to download your Double-sided upgrade file from your online support account and transfer it to a computer connected to your Ultima printer via USB.

Begiater product		Double-side	d upgrade keys			
Products		-				
Promite	- <u>\$</u>)	ALL GENERATED				
300 A Sprinter	1					
Hein:	. 4					
Rip Pro	1					
Endance	1.4	Non-Address	formable midlert concrede	Deschief sector	VODERNY	
Double sided apgrade keys	<u></u>	wey name.	for serial X000000	Propuls sense.	100000	
lases		Status	Constated	Type	DoubleSided	
Create new support case	- 33	Creatiest.	00 Agy 2016 10:30 00	updated.	06 Apr 2016 11:05:40	
Closed names	17	readiat	🖵 uzikteolootai	103911170306c4	etien2.upg (application/or	tet-stream)
HoloKotes		Continues				
Create new HoloKote						
restorcobe literary						
Ay Account						
Your account details						
Champe personni 1						
the second s						

Save this file to a known location such as the **<Desktop>** or **<My documents>** area of the computer connect to the Ultima printer.

Next open the Magicard Ultima driver in the **<Devices and printers>** area of your Windows OS and then open **<Adjust printer options>**

← Settings	-	>
வ Magicard Ultima (V2)		
Manage your device		
Printer status: Idle		
Open print queue Set as default		
Print a test page		
Run the troubleshooter		
Printer properties		
Printing preferences		
Hardware properties		
Have a question? Get help		

On the first <Printer tab> click <Printer upgrade(s)...> button

Hagicard Ultima (V2) Printing Prefere	ences	×
MAGICARDUIt	ima	Ē
Printer	Duplex printing	Front only
= • Card front	Card orientation	Landscape ~
	Card size	CR80 card ~
Card back		Bend Solution
Encoding		1036 x 664 pixels
Image		87.7 x 56.1 mm
Advanced	Number of copies	1
Save	Printer upgrade(s)	Printer status
About Help		OK Cancel Apply

Click on **<Offline install>.** Navigate to the file location of your saved printer upgrade file (.Upg).



You will receive a confirmation message when the printer has been upgraded



To check your printer has been successfully upgraded navigate to your **<printer tab>** and the **<Duplex printing option>** will be enabled as well as the **<Card back tab>** in the printer driver.

	tima	
Printer	Duplex printing	Front only ~
Card front	Card orientation Card size	Landscape v CR80 card v
Card back	1	Bend Solution
Encoding		1036 x 664 pixels 3.453 x 2.213 inches
Image		87.7 x 56.1 mm
Advanced	Number of copies	1 *
Save	Printer upgrade(s)	Printer status
About Help		OK Cancel Apply